

# CENTURION RT

6000VA | 10kVA



The Centurion RT features true online double conversion. As our highest single phase power density UPS, this sophisticated range will provide the most comprehensive protection for mission critical devices such as sensitive networks, computers, servers, telecom applications, as well as industrial applications. Meticulously developed by PowerShield engineers to be a world leading technology UPS, the Centurion RT addresses absolutely all requirements and features as has been demanded by the sophisticated Australian power consumer and hence stands in a class of its own, as a world leading UPS technology.

## FEATURES

### EXCEPTIONAL SURGE PROTECTION

Offering the best surge protection in its class to protect against damaging surges.

### UNITY OUTPUT POWER FACTOR (PF=1)

The Centurion RT is a high-density UPS with unity output power factor (PF=1) to provide higher performance and efficiency to critical applications.

### INFORMATIVE & EASY-SHIFT LCD DISPLAY

The front panel LCD display panel is readily viewable whether the UPS is horizontal or vertical, displaying all critical & non-critical parameters, including remaining battery backup time.

### RACK/TOWER DESIGN

The Centurion RT can be easily installed as a floor-standing tower or in a 19-inch rack.

High power density means that both the UPS and the battery bank are only 2RU height each.

### EMERGENCY POWER OFF FUNCTION (EPO)

This feature can turn off and isolate the UPS in the event of fires or other emergencies

### ECO & ADVANCED ECO MODE

It has an advanced ECO mode, which allows the UPS to operate at a very high efficiency, up to 98%. When the utility mains input voltage is within the ECO range the UPS saves energy by passing the mains supply directly through to the load, while the inverter continues to operate in a passive mode

### HOT SWAPPABLE BATTERIES

Battery banks are hot-swappable, keeping the UPS operational during battery replacement. Additional battery banks can be added to increase battery backup time.

### HID COMMUNICATION VIA USB

HID can be used for simple management with Windows, Apple, Linux and NAS devices and a large variety of industrial controllers that support HID.

HID ensures a safe and orderly shutdown in the event of a prolonged power outage.

### NETGUARD SOFTWARE COMMUNICATION VIA USB

The free, downloadable NetGuard software provides complete power monitoring. Parameters such as input/output voltage, battery capacity and load level are easily viewed. It also ensures a safe and orderly shutdown in the event of a prolonged outage.

### STANDARD EXTRA LARGE CHARGER

The Centurion RT has been designed with a larger charger than other UPSs ensuring rapid recharge times when adding additional battery banks. Larger charger allows for easy addition of extra battery banks

### OPTIONAL ACCESSORIES

- PSSNMPV4 – NMP card (option to connect a PSEMD)
- PSEMD – Environmental Monitoring Device for temperature and humidity
- PSModbus – Modbus card
- PSAS400 – AS400 dry contact card
- PSRK – 1RU rail kit
- PSRTBB16, PSCERBB20 – Extra battery modules
- PSMSBR10K – Maintenance Bypass Switches
- PSPDU10K – 10KVA PDU with 10A IEC 320 C13 (x8), 16A IEC 320 C19 (x4)



AUSTRALIAN DESIGNED  
POWER PROTECTION  
SOLUTIONS



CENTURION RT RANGE (6K–10K)					
MODEL		CENTURION RT 6000L	CENTURION RT 10KL	STANDARD RT BATTERY BANK	OPTIONAL RACK BATTERY BANK
Model Number		PSCERT6000L	PSCERT10KL	PSRTBB16	PSCERBB20
Capacity		6000VA/6000W	10kVA/10kW	Suits PSCERT6000L & PSCERT10KL	
Topology		True online double-conversion, Pure Sine Wave			
INPUT					
Voltage Range	Line Loss	110–300Vac @ (0–60%) Load; 140–300V @ (60–80%) Load; 176–300VAC @ (80–100%) Load			
	Low Line Comeback	Low Line Loss Voltage + 10V			
	High Line Comeback	High Line Loss Voltage – 10V			
Frequency Range		46Hz–54 Hz @ 50Hz system; 56Hz–64 Hz @ 60Hz system			
Phase		Single phase with ground			
Input Power Factor Correction		0.99 @ nominal voltage (100% load)			
OUTPUT					
Output Voltage		240VAC (Selectable 208 / 220 / 230 / 240VAC)			
AC Voltage Regulation		± 1%			
Frequency Range (Synchronized Range)		46Hz–54 Hz @ 50Hz system 56Hz–64 Hz @ 60Hz system			
Frequency Range (Batt. Mode)		50 Hz ± 0.1 Hz or 60Hz ± 0.1 Hz			
Overload	AC Mode	100%–110%: 10min ; 110%–130%: 1min ; >130% : 1sec			
	Battery Mode	100%–110%: 30sec ; 110%–130%: 10sec ; >130% : 1sec			
Current Crest Ration		3:1 Max			
Harmonic Distortion		1 % @ 100% Linear Load; 4% @ 100% Non-linear Load			
Transfer Time	Line to Battery	0 ms			
	Inverter to Bypass	0 ms			
	Inverter to Eco	< 10 ms			
Outlets		Hard wired terminal input / output. IEC outlets with PSPDU10K PDU.			
EFFICIENCY					
AC Mode		> 94%			
Battery Mode		> 93%			
BATTERY					
Battery Banks		PSRTBB16 (standard), PSCERBB20 (optional). Customised options available			
Battery Number		Batteries are 12Vdc. Customised optional strings of 16, 18, 20		x 16	x 20
Typical Recharge Time		4 hours for PSRTBB16 and PSCERBB20			
Charging Current (max.)		4 A ± 10%			
COMMUNICATIONS AND MANAGEMENT					
Interface		USB and RS232 as standard			
Software		PowerShield® NetGuard® software – supports Windows, Linux, Unix and Mac based operating systems			
HID		Supports Windows, Apple, Linux, NAS and various industrial controllers			
Optional		Intelligent slot for PSSNMPV4, PSModbus or PSAS400 dry contact			
PHYSICAL					
Dimension, (D x W x H) mm		UPS Unit: 655 x 438 x 88 [2U] 17kg	UPS Unit: 655 x 438 x 88 [2U] 20kg	733 x 438 x 88 [2U]	580 x 438 x 133 [3U]
Weight (kg)		13.5	16	54	57
OPERATING ENVIRONMENT					
Temperature		0–40°C			
Humidity		95% (RH Non-condensing)			
Altitude		< 1000m			
Noise Level		< 55dB @ 1 Meter	< 58dB @ 1 Meter		

Product specifications are subject to change without notice. Derate capacity to 60% in CVCF mode. Derate capacity to 90% when the output voltage is adjusted to 208VAC. If the UPS is installed or used in a place where the altitude is above 1000m, the output power must be derated one percent per 100m.

Power Factor = 1 when using 20 battery string; Power Factor = 0.9 when using 18 battery string; Power Factor = 0.8 when using 16 battery string.

## REAR VIEW

Rear PSCERT 6000L and 10KL



Rear Battery Pack PSRTBB16

